

QuickSpecs

HPE FlexNetwork 5510 HI Switch Series

Overview

HPE FlexNetwork 5510 HI Switch Series



Models

HPE 5510 24G 4SFP+ HI 1-slot Switch	JH145A
HPE 5510 48G 4SFP+ HI 1-slot Switch	JH146A
HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch	JH147A
HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch	JH148A
HPE 5510 24G SFP 4SFP+ HI 1-slot Switch	JH149A

Key features

- Scalable with 10 Gigabit uplinks and 9-chassis IRF with up to 160 GB/s stacking bandwidth
- 40G QSFP+ ports for uplink or stacking
- 4 convenient built-in SFP+ 10GbE uplinks provide performance for bandwidth hungry applications
- PoE+ for up to 30 Watts of PoE power per port on all ports simultaneously
- MACsec support

Product overview

The HPE FlexNetwork 5510 HI Switch Series comprises Gigabit Ethernet switches that deliver outstanding resiliency, security, and multiservice support capabilities at the edge layer of data center, large campus, and metro Ethernet networks. The switches can also be used in the core layer of SMB networks.

With Intelligent Resilient Fabric (IRF) support and available dual power supplies, the HPE FlexNetwork 5510 HI Series Switch can deliver the highest levels of resiliency and manageability. In addition, the PoE+ models provide up to 1440 W of PoE+ power with the dual power supply configuration.

Designed with four fixed 10GbE ports and supports additional modular uplinks, these switches can provide up to six 10GbE uplink ports. With complete IPv4/IPv6, OpenFlow, and MPLS/VPLS features, the series provides investment protection with an easy transition from IPv4 to IPv6 networks.

Features and benefits

Software-defined networking

- OpenFlow

QuickSpecs**Overview**

supports OpenFlow 1.3 specification to enable SDN by allowing separation of the data (packet forwarding) and control (routing decision) paths

Quality of Service (QoS)

- **Advanced classifier-based QoS**
classifies traffic using multiple match criteria based on Layer 2, 3, and 4 information; applies QoS policies such as setting priority level and rate limit to selected traffic on a per-port or per-VLAN basis
- **Traffic policing**
supports Committed Access Rate (CAR) and line rate
- **Powerful QoS feature**
creates traffic classes based on access control lists (ACLs), IEEE 802.1p precedence, IP, and DSCP or Type of Service (ToS) precedence; supports filter, redirect, mirror, or remark; supports the following congestion actions: strict priority (SP) queuing, weighted round robin (WRR), weighted fair queuing (WFQ), weighted random early discard (WRED), weighted deficit round robin (WDRR), SP+WDRR, and SP+WFQ
- **Storm restraint**
allows limitation of broadcast, multicast, and unknown unicast traffic rate to reduce unwanted broadcast traffic on the network
- **Broadcast control**
allows limitations of broadcast traffic rate to cut down on unwanted network broadcast traffic

Management

- **Friendly port names**
allows assignment of descriptive names to ports
- **sFlow (RFC 3176)**
provides scalable ASIC-based wirespeed network monitoring and accounting with no impact on network performance; this allows network operators to gather a variety of sophisticated network statistics and information for capacity planning and real-time network monitoring purposes
- **Complete session logging**
provides detailed information for problem identification and resolution
- **Remote configuration and management**
enables configuration and management through a secure Web browser or a CLI located on a remote device
- **Manager and operator privilege levels**
provides read-only (operator) and read/write (manager) access on CLI and Web browser management interfaces
- **Management VLAN**
segments traffic to and from management interfaces, including CLI/Telnet, a Web browser interface, and SNMP
- **Command authorization**
leverages RADIUS/HWTACACS to link a custom list of CLI commands to an individual network administrator's login; also provides an audit trail
- **Secure Web GUI**
provides a secure, easy-to-use graphical interface for configuring the module via HTTPS
- **Remote monitoring (RMON)**
uses standard SNMP to monitor essential network functions; supports events, alarm, history, and statistics group plus a private alarm extension group
- **Multiple configuration files**
stores easily to the flash image
- **Remote intelligent mirroring**
mirrors ingress/egress ACL-selected traffic from a switch port or VLAN to a local or remote switch port anywhere on the network
- **In-service software upgrade (ISSU)**
enables operators to perform upgrades in the shortest possible amount of time with reduced risk to network operations or traffic disruptions

QuickSpecs**Overview**

- **Network Management**
SNMP v1/v2c/v3, MIB-II with Traps, and RADIUS Authentication Client MIB (RFC 2618); embedded HTML management tool with secure access
- **IPv6 management**
provides future-proof networking because the switch is capable of being managed whether the attached network is running IPv4 or IPv6; supports pingv6, tracertv6, Telnetv6, TFTPV6, DNSv6, syslogv6, FTPv6, SNMPv6, DHCPv6, and RADIUS for IPv6}
- **Troubleshooting**
ingress and egress port monitoring enables network problem-solving; virtual cable tests provide visibility into cable problems
- **HPE Intelligent Management Center (IMC)**
integrates fault management, element configuration, and network monitoring from a central vantage point; built-in support for third-party devices enables network administrators to centrally manage all network elements with a variety of automated tasks, including discovery, categorization, baseline configurations, and software images; the software also provides configuration comparison tools, version tracking, change alerts, and more

Connectivity

- **Auto-MDIX**
automatically adjusts for straight-through or crossover cables on all 10/100/1000 ports
- **Packet storm protection**
protects against broadcast, multicast, or unicast storms with user-defined thresholds
- **Ethernet operations, administration and maintenance (OAM)**
detects data link layer problems that occurred in the "last mile" using the IEEE 802.3ah OAM standard; monitors the status of the link between two devices
- **Flow control**
provides back pressure using standard IEEE 802.3x, reducing congestion in heavy traffic situations
- **Fixed 10GbE ports**
provides four fixed SFP+ ports for a 20 GbE connection to the network without the need for additional extension interface modules
- **Optional 10GbE or 40GbE ports**
deliver, through the use of optional modules, additional 10GbE or 40GbE connections, which are available for uplinks or high-bandwidth server connections; flexibly support copper, SFP+, or 40GbE QSFP+ connections
- **Jumbo packet support**
supports up to 10000-byte frame size to improve the performance of large data transfers
- **IEEE 802.3at Power over Ethernet (PoE+)**
provides up to 30 W per port that allows support of the latest PoE+-capable devices such as IP phones, wireless access points, and security cameras, as well as any IEEE 802.3af-compliant end device; eliminates the cost of additional electrical cabling and circuits that would otherwise be necessary in IP phone and WLAN deployments

Performance

- **Hardware-based wirespeed access control lists (ACLs)**
help provide high levels of security and ease of administration without impacting network performance with a feature-rich TCAM-based ACL implementation
- **Nonblocking architecture**
delivers up to 336 Gb/s of wire-speed switching with a nonblocking switching fabric and up to 250 million pps throughput

Resiliency and high availability

- **Separate data and control paths**
separates control from services and keeps service processing isolated; increases security and performance

QuickSpecs**Overview**

- **Device Link Detection Protocol (DLDP)**
monitors link connectivity and shuts down ports at both ends if unidirectional traffic is detected, preventing loops in STP-based networks
- **Intelligent Resilient Fabric (IRF)**
creates virtual resilient switching fabrics, where two to nine switches perform as a single L2 switch and L3 router; switches do not have to be co-located and can be part of a disaster-recovery system; servers or switches can be attached using standard LACP for automatic load balancing and high availability; can eliminate need for complex protocols like Spanning Tree Protocol, Equal-Cost Multipath (ECMP), or VRRP, thereby simplifying network operation
- **Rapid Ring Protection Protocol (RRPP)**
connects multiple switches in a high-performance ring using standard Ethernet technology; traffic can be rerouted around the ring in less than 50 ms, reducing the impact on traffic and applications
- **Smart Link**
Allows under 100ms failover between links
- **Virtual Router Redundancy Protocol (VRRP)**
allows groups of two routers to dynamically back each other up to create highly available routed environments
- **IRF Capability**
provides single IP address management for a resilient virtual switching fabric of up to nine switches using up to 160 Gb/s bidirectional using QSFP+ links
- **Spanning Tree/PVST+, MSTP, RSTP**
provides redundant links while preventing network loops
- **Internal Dual Redundant Power Supply**
provides high reliability by keeping network up while delivering up to 1440 Watts of PoE+

Manageability

- **Dual flash images**
provides independent primary and secondary operating system files for backup while upgrading
- **Multiple configuration files**
allow multiple configuration files to be stored to a flash image
- **Troubleshooting**
allows ingress and egress port monitoring, enabling network problem solving; virtual cable tests provide visibility into cable problems
- **IPv6 management**
future-proofs networking, as the switch is capable of being managed whether the attached network is running IPv4 or IPv6; supports pingv6, tracertv6, Telnetv6, TFTPv6, DNSv6, and ARPv6

Layer 2 switching

- **GARP VLAN Registration Protocol**
allows automatic learning and dynamic assignment of VLANs
- **IP multicast snooping and data-driven IGMP**
automatically prevents flooding of IP multicast traffic
- **Internet Group Management Protocol (IGMP) and Multicast Listener Discovery (MLD) protocol snooping**
controls and manages the flooding of multicast packets in a Layer 2 network
- **32K MAC addresses**
provide access to many Layer 2 devices
- **IEEE 802.1ad QinQ and selective QinQ**
increase the scalability of an Ethernet network by providing a hierarchical structure; connect multiple LANs on a high-speed campus or metro network
- **10GbE port aggregation**
allows grouping of ports to increase overall data throughput to a remote device
- **Spanning Tree/MSTP, RSTP, and STP root guard**

QuickSpecs**Overview**

- prevent network loops
- **64 MSTP instances**
allow multiple configurations of STP per VLAN group
- **Isolation at data link layer with private VLANs**
provides, through a two-tier VLAN structure, an additional layer of protection, simplifying network configuration while saving VLAN resources
- **VLAN support and tagging**
supports the IEEE 802.1Q (4094 VLAN IDs)

Layer 3 services

- **Address Resolution Protocol (ARP)**
determines the MAC address of another IP host in the same subnet; supports static ARPs; gratuitous ARP allows detection of duplicate IP addresses; proxy ARP allows normal ARP operation between subnets or when subnets are separated by a Layer 2 network
- **Dynamic Host Configuration Protocol (DHCP)**
simplifies the management of large IP networks; supports client; DHCP Relay enables DHCP operation across subnets
- **Loopback interface address**
defines an address that can always be reachable, improving diagnostic capability
- **User Datagram Protocol (UDP) helper function**
allows UDP broadcasts to be directed across router interfaces to specific IP unicast or subnet broadcast addresses and prevents server spoofing for UDP services such as DHCP
- **Route maps**
provide more control during route redistribution; allow filtering and altering of route metrics
- **DHCP server**
centralizes and reduces the cost of the IPv4 address management

Layer 3 routing

- **IPv4 routing protocols**
support static routes, RIP, OSPF, ISIS, and BGP
- **IPv6 routing protocols**
provide routing of IPv6 at wire speed; support static routes, RIPng, OSPFv3, IS-ISv6, and BGP4+ for IPv6
- **PIM-SSM, PIM-DM, and PIM-SM (for IPv4 and IPv6)**
support IP Multicast address management and inhibition of DoS attacks
- **MPLS support**
provides extended support of MPLS, including MPLS VPNs and MPLS Traffic Engineering (MPLS TE)
- **Virtual Private LAN Service (VPLS)**
establishes point-to-multipoint Layer 2 VPNs across a provider network
- **Bidirectional Forwarding Detection (BFD)**
enables link connectivity monitoring and reduces network convergence time for RIP, OSPF, BGP, IS-IS, VRRP, MPLS, and IRF
- **Policy-based routing**
makes routing decisions based on policies set by the network administrator
- **Equal-Cost Multipath (ECMP)**
enables multiple equal-cost links in a routing environment to increase link redundancy and scale bandwidth
- **IPv6 tunneling**
allows a smooth transition from IPv4 to IPv6 by encapsulating IPv6 traffic over an existing IPv4 infrastructure

Security

- **Access control lists (ACLs)**

QuickSpecs**Overview**

provide IP Layer 2 to Layer 4 traffic filtering; support global ACL, VLAN ACL, port ACL, and IPv6 ACL; up to 6144 ingress ACLs and 1024 egress ACLs are supported

- **IEEE 802.1X**
defines an industry-standard method of user authentication using an IEEE 802.1X supplicant on the client in conjunction with a RADIUS server
- **MAC-based authentication**
client is authenticated with the RADIUS server based on the client's MAC address
- **Identity-driven security and access control**
 - **Per-user ACLs**
permits or denies user access to specific network resources based on user identity and time of day, allowing multiple types of users on the same network to access specific network services without risking network security or providing unauthorized access to sensitive data
 - **Automatic VLAN assignment**
automatically assigns users to the appropriate VLAN based on their identities
- **Port security**
allows access only to specified MAC addresses, which can be learned or specified by the administrator
- **Secure FTP/ SCP**
allows secure file transfer to and from the switch; protects against unwanted file downloads or unauthorized copying of a switch configuration file
- **STP BPDU port protection**
blocks Bridge Protocol Data Units (BPDUs) on ports that do not require BPDUs, preventing forged BPDU attacks
- **DHCP protection**
blocks DHCP packets from unauthorized DHCP servers, preventing denial-of-service attacks
- **DHCP snooping**
helps ensure that DHCP clients receive IP addresses from authorized DHCP servers and maintain a list of DHCP entries for trusted ports; prevents reception of fake IP addresses and reduces ARP attacks, improving security
- **DHCPv6 snooping**
ensures that DHCPv6 clients obtain IPv6 addresses from authorized DHCPv6 servers and record IP-to-MAC mappings of DHCPv6 clients
- **Dynamic ARP protection**
blocks ARP broadcasts from unauthorized hosts, preventing eavesdropping or theft of network data
- **STP root guard**
protects the root bridge from malicious attacks or configuration mistakes
- **Guest VLAN**
provides a browser-based environment to authenticated clients that is similar to IEEE 802.1X
- **Port isolation**
secures and adds privacy, and prevents malicious attackers from obtaining user information
- **Endpoint Admission Defense (EAD)**
provides security policies to users accessing a network
- **RADIUS/HWTACACS**
eases switch management security administration by using a password authentication server
- **Secure management access**
delivers secure encryption of all access methods (CLI, GUI, or MIB) through SSHv2, SSL, HTTPS and/or SNMPv3
- **Unicast Reverse Path Forwarding (URPF)**
allows normal packets to be forwarded correctly, but discards the attaching packet due to lack of reverse path route or incorrect inbound interface; prevents source spoofing and distributed attacks; supports distributed UPFF
- **IP source guard**
helps prevent IP spoofing attacks
- **IPv6 source guard**
help prevent IPv6 spoofing attacks using ND Snooping as well as DHCPv6 Snooping
- **ND Snooping**
allows only packets with a legally obtained IPv6 address to pass

QuickSpecs**Overview****Virtual private network (VPN)**

- **Generic Routing Encapsulation (GRE)**

transports Layer 2 connectivity over a Layer 3 path in a secured way; enables the segregation of traffic from site to site

Convergence

- **LLDP-MED (Media Endpoint Discovery)**

defines a standard extension of LLDP that stores values for parameters such as QoS and VLAN to automatically configure network devices such as IP phones

- **Internet Group Management Protocol (IGMP)**

utilizes Any-Source Multicast (ASM) or Source-Specific Multicast (SSM) to manage IPv4 multicast networks; supports IGMPv1, v2, and v3

- **IEEE 802.1AB Link Layer Discovery Protocol (LLDP)**

facilitates easy mapping using network management applications with LLDP automated device discovery protocol

- **Multicast Source Discovery Protocol (MSDP)**

allows multiple PIM-SM domains to interoperate; is used for inter-domain multicast applications

- **Multicast VLAN**

allows multiple VLANs to receive the same IPv4 or IPv6 multicast traffic, lessening network bandwidth demand by reducing or eliminating multiple streams to each VLAN

- **LLDP-CDP compatibility**

receives and recognizes CDP packets from Cisco's IP phones for seamless interoperation

- **IEEE 802.3at Power over Ethernet (PoE+)**

provides up to 30 W per port that allows support of the latest PoE+-capable devices such as IP phones, wireless access points, and security cameras, as well as any IEEE 802.3af-compliant end device; eliminates the cost of additional electrical cabling and circuits that would otherwise be necessary in IP phone and WLAN deployments

- **PoE allocations**

supports multiple methods (automatic, IEEE 802.3af class, LLDP-MED, or user-specified) to allocate PoE power for more efficient energy savings

- **Voice VLAN**

automatically assigns VLAN and priority for IP phones, simplifying network configuration and maintenance

- **IP multicast snooping (data-driven IGMP)**

prevents flooding of IP multicast traffic

Additional information

- **Green initiative support**

provides support for RoHS and WEEE regulations

- **Green IT and power**

improves energy efficiency through the use of the latest advances in silicon development; shuts off unused ports and utilizes variable-speed fans, reducing energy costs

- **Unified Hewlett Packard Enterprise Comware operating system with modular architecture**

provides an easy-to-enhance-and-extend feature set, which doesn't require whole-scale changes; all switching, routing, and security platforms leverage the Comware OS, a common unified modular operating system

- **Energy Efficient Ethernet (EEE) support**

Reduces power consumption in accordance with IEEE 802.3az

Warranty and support

- **Limited Lifetime Warranty**

See <http://www.hpe.com/networking/warrantysummary> for warranty and support information included with your product purchase.

QuickSpecs**Overview**

- **Software releases**

to find software for your product, refer to <http://www.hpe.com/networking/support>; for details on the software releases available with your product purchase, refer to <http://www.hpe.com/networking/warrantysummary>

QuickSpecs**Configuration**

Build To Order: BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

Switch Chassis

HPE 5510 24G 4SFP+ HI 1-slot Switch

JH145A

- 24 RJ-45 autosensing 10/100/1000 ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration

NOTE: 2

HPE 5510 48G 4SFP+ HI 1-slot Switch

JH146A

- 48 RJ-45 autosensing 10/100/1000 ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration

NOTE: 2

HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch

JH147A

- 24 RJ-45 autosensing 10/100/1000 PoE+ ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration

NOTE: 2

HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch

JH148A

- 48 RJ-45 autosensing 10/100/1000 PoE+ ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration

NOTE: 2, 3

HPE 5510 24G SFP 4SFP+ HI 1-slot Switch

JH149A

- 16 SFP fixed Gigabit Ethernet SFP ports (min=0 \ max=16 SFP Transceivers)
- 8 RJ-45/ SFP fixed combo ports (min=0 \ max=8 SFP Transceivers)
- 4 fixed SFP+ ports (min=0 \ max=4 SFP+ Transceivers)
- 1 open module slots, or a combination
- Must select min 1 power supply
- 1U - Height

See Configuration

NOTE: 1, 2**Configuration Rules:**

QuickSpecs**Configuration****Note 1****The following Transceivers install into this Switch: (SFP Ports)**

HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A

Note 2**The following Transceivers install into this Switch: (SFP+ Ports)**

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C

Note 3**The following LC Transceiver install into this switch:**

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
---	--------

Remarks:

Iris note - If the below cables are selected for the JH146A and JH148A, then 4 RJ 45 ports are disabled:

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

Box Level Integration CTO Models**CTO Solution SKU**

QuickSpecs**Configuration**

HPE FlexNetwork 55xx Configure-to-order Switch Solution

JG506A

- SSP trigger SKU

CTO Switch Chassis

HPE 5510 24G 4SFP+ HI 1-slot Switch

JH145A

- 24 RJ-45 autosensing 10/100/1000 ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration
NOTE: 2, 10

HPE 5510 48G 4SFP+ HI 1-slot Switch

JH146A

- 48 RJ-45 autosensing 10/100/1000 ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration
NOTE: 2, 10

HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch

JH147A

- 24 RJ-45 autosensing 10/100/1000 PoE+ ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration
NOTE: 2, 10

HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch

JH148A

- 48 RJ-45 autosensing 10/100/1000 PoE+ ports
- 4 fixed Gigabit Ethernet SFP+ ports
- (min=0 \ max=4 SFP/SFP+ Transceivers)
- 1 port expansion module slots
- Must select min 1 power supply
- 1U - Height

See Configuration
NOTE: 2, 3, 10

HPE 5510 24G SFP 4SFP+ HI 1-slot Switch

JH149A

- 16 SFP fixed Gigabit Ethernet SFP ports (min=0 \ max=16 SFP Transceivers)
- 8 RJ-45/ SFP fixed combo ports (min=0 \ max=8 SFP Transceivers)
- 4 fixed SFP+ ports (min=0 \ max=4 SFP+ Transceivers)
- 1 open module slots, or a combination
- Must select min 1 power supply
- 1U - Height

See Configuration
NOTE: 1, 2, 10

Configuration Rules:**Note 1****The following Transceivers install into this Switch: (SFP Ports)**

HPE X115 100M SFP LC FX Transceiver
HPE X110 100M SFP LC LX Transceiver

JD102B
JD120B

QuickSpecs**Configuration**

HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A

Note 2**The following Transceivers install into this Switch: (SFP+ Ports)**

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C

Note 3**The following LC Transceiver install into this switch:**

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
---	--------

Note 10

If the Switch Chassis is to be Factory Integrated (CTO), Then the #0D1 is required on the Switch Chassis and integrated to the JG506A - HPE 55xx CTO Switch Solution. (Min 1/Max 1 Switch per SSP)

Remarks:

Iris note - If the below cables are selected for the JH146A and JH148A, then 4 RJ 45 ports are disabled:

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

Rack Level Integration CTO Models**Switch Chassis**

QuickSpecs**Configuration**

HPE 5510 24G 4SFP+ HI 1-slot Switch	JH145A See Configuration NOTE: 2, 10
<ul style="list-style-type: none"> • 24 RJ-45 autosensing 10/100/1000 ports • 4 fixed Gigabit Ethernet SFP+ ports • (min=0 \ max=4 SFP/SFP+ Transceivers) • 1 port expansion module slots • Must select min 1 power supply • 1U - Height 	
HPE 5510 48G 4SFP+ HI 1-slot Switch	JH146A See Configuration NOTE: 2, 10
<ul style="list-style-type: none"> • 48 RJ-45 autosensing 10/100/1000 ports • 4 fixed Gigabit Ethernet SFP+ ports • (min=0 \ max=4 SFP/SFP+ Transceivers) • 1 port expansion module slots • Must select min 1 power supply • 1U - Height 	
HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch	JH147A See Configuration NOTE: 2, 10
<ul style="list-style-type: none"> • 24 RJ-45 autosensing 10/100/1000 PoE+ ports • 4 fixed Gigabit Ethernet SFP+ ports • (min=0 \ max=4 SFP/SFP+ Transceivers) • 1 port expansion module slots • Must select min 1 power supply • 1U - Height 	
HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch	JH148A See Configuration NOTE: 2, 3, 10
<ul style="list-style-type: none"> • 48 RJ-45 autosensing 10/100/1000 PoE+ ports • 4 fixed Gigabit Ethernet SFP+ ports • (min=0 \ max=4 SFP/SFP+ Transceivers) • 1 port expansion module slots • Must select min 1 power supply • 1U - Height 	
HPE 5510 24G SFP 4SFP+ HI 1-slot Switch	JH149A See Configuration NOTE: 1, 2, 10
<ul style="list-style-type: none"> • 16 SFP fixed Gigabit Ethernet SFP ports (min=0 \ max=16 SFP Transceivers) • 8 RJ-45/ SFP fixed combo ports (min=0 \ max=8 SFP Transceivers) • 4 fixed SFP+ ports (min=0 \ max=4 SFP+ Transceivers) • 1 open module slots, or a combination • Must select min 1 power supply • 1U - Height 	

Configuration Rules:**Note 1 The following Transceivers install into this Switch: (SFP Ports)**

HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A

QuickSpecs**Configuration**

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH100 Transceiver	JD103A

Note 2**The following Transceivers install into this Switch: (SFP+ Ports)**

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C

Note 3**The following LC Transceiver install into this switch:**

HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
---	--------

Note 10

If HPE CTO Switch Chassis is selected for Rack Level Integration, Then the Switch needs to integrate (with #0D1) to the Rack.

Remarks:

No Rail Kit required

Iris note - If the below cables are selected for the JH146A and JH148A, then 4 RJ 45 ports are disabled:

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

Enter the following menu selections as integrated to the CTO Model X above if order is factory built.

Modules**System (std 0 // max 1) User Selection (min 0 // max 1)**

HPE 5130/5510 10GBASE-T 2-port Module

JH156A

QuickSpecs**Configuration**

- No Transceivers

HPE 5130/5510 10GbE SFP+ 2-port Module JH157A
 • min=0 \ max=2 SFP+ Transceivers See Configuration
NOTE: 1

HPE 5510 2-port QSFP+ Module JH155A
 • min=0 \ max=2 QSFP+ Transceivers See Configuration
NOTE: 2

Configuration Rules:**Note 1****The following Transceivers install into this Module (SFP+ Ports)**

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC LH80 tunable XCVR	JL250A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A

Note 2**The following 40G Transceivers install into this Module: (Use #0D1 or #B01 if switch is CTO)**

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

Transceivers**SFP Transceivers**

HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X125 1G SFP LC LH70 Transceiver	JD063B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X120 1G SFP LC LH100 Transceiver	JD103A
HPE X125 1G SFP LC LH40 1310nm Transceiver	JD061A
HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver	JD098B

QuickSpecs**Configuration**

HPE X120 1G SFP LC BX 10-D Transceiver	JD099B
HPE X115 100M SFP LC BX 10-U Transceiver	JD100A
HPE X115 100M SFP LC FX Transceiver	JD102B
HPE X110 100M SFP LC LX Transceiver	JD120B
HPE X115 100M SFP LC BX 10-D Transceiver	JD101A
HPE X110 100M SFP LC LH40 Transceiver	JD090A
HPE X110 100M SFP LC LH80 Transceiver	JD091A

SFP+ Transceivers

HPE X130 10G SFP+ LC ER 40km Transceiver	JG234A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LRM Transceiver	JD093B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C

QSFP+ Transceivers

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

Cables**Multi-Mode Cables**

HPE LC to LC Multi-mode OM3 2-Fiber 0.5m 1-Pack Fiber Optic Cable	AJ833A
HPE LC to LC Multi-mode OM3 2-Fiber 1.0m 1-Pack Fiber Optic Cable	AJ834A
HPE LC to LC Multi-mode OM3 2-Fiber 2.0m 1-Pack Fiber Optic Cable	AJ835A
HPE LC to LC Multi-mode OM3 2-Fiber 5.0m 1-Pack Fiber Optic Cable	AJ836A
HPE LC to LC Multi-mode OM3 2-Fiber 15.0m 1-Pack Fiber Optic Cable	AJ837A
HPE LC to LC Multi-mode OM3 2-Fiber 30.0m 1-Pack Fiber Optic Cable	AJ838A
HPE LC to LC Multi-mode OM3 2-Fiber 50.0m 1-Pack Fiber Optic Cable	AJ839A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 1m Cable	QK732A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 2m Cable	QK733A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 5m Cable	QK734A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 15m Cable	QK735A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 30m Cable	QK736A

QuickSpecs**Configuration**

HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 50m Cable

QK737A

Internal Power Supplies

System (std 0 // max 2) User Selection (min 1 // max 2) per switch enclosure

HPE FlexNetwork 5500 150WDC Power Supply

JD366A

See Configuration

NOTE: 1

HPE FlexNetwork 5500 150WAC Power Supply 4

JD362A

See Configuration

NOTE: 1, 3, 4

PDU Cable NA/MEX/TW/JP

JD362A#B2B

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

PDU Cable ROW

JD362A#B2C

- C15 PDU Jumper Cord (ROW)

High Volt Switch to Wall Power Cord

JD362A#B2E

- NEMA L6-20P Cord (NA/MEX/JP/TW)

HPE X362 720W 100-240VAC to 56VDC PoE Power Supply

JG544A

See Configuration

NOTE: 2, 3, 4

PDU Cable NA/MEX/TW/JP

JG544A#B2B

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

PDU Cable ROW

JG544A#B2C

- C15 PDU Jumper Cord (ROW)

High Volt Switch to Wall Power Cord

JG544A#B2E

- NEMA L6-20P Cord (NA/MEX/JP/TW)

HPE X362 1110W 115-240VAC to 56VDC PoE Power Supply

JG545A

See Configuration

NOTE: 2, 3, 4

PDU Cable NA/MEX/TW/JP

JG545A#B2B

- C15 PDU Jumper Cord (NA/MEX/TW/JP)

PDU Cable ROW

JG545A#B2C

- C15 PDU Jumper Cord (ROW)

High Volt Switch to Wall Power Cord

JG545A#B2E

- NEMA L6-20P Cord (NA/MEX/JP/TW)

QuickSpecs**Configuration****Configuration Rules:**

- Note 1** This power supply is only supported on JH145A, JH146A, and JH149A
- Note 2** This power supply is only supported on JH147A and JH148A,
- Note 3** Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord). (See Localization Menu)
- Note 4** When Switches/Routers are Factory Racked, Then #B2B, or #B2C should be the Defaulted Power Cable option on the Switches/Routers.

Remarks: Drop down under power supply should offer the following options and results:
Switch/Router/Power Supply to PDU Power Cord - #B2B in North America, Mexico, Taiwan, and Japan or #B2C ROW. (Watson Default B2B or B2C for Rack Level CTO)
Switch/Router/Power Supply to Wall Power Cord - Localized Option (Watson Default for BTO and Box Level CTO)
High Volt Switch/Router/Power Supply to Wall Power Cord - #B2E Option. (Offered only in North America, Mexico, Taiwan, and Japan)
NOTE* DC Power Supply does not require Localization (CLIC Rule does not require looking for Localization)
NOTE* Mixing of power supplies is supported

QuickSpecs**Technical Specifications****HPE 5510 24G 4SFP+ HI 1-slot Switch (JH145A)**

I/O ports and slots	24 RJ-45 autosensing 10/100/1000 ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T); Media Type: Auto-MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only; Ports 1 - 8 support MACSec 4 SFP+ 10GbE ports 1 port expansion module slot Supports a maximum of 6 SFP+ ports or 2 1/10GBASE-T ports or 2 40GbE ports, with optional module
Additional ports and slots	1 dual-personality (RJ-45 or USB micro-B) serial console port 1 RJ-45 out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	Airflow direction is Front (port side) to Back (power cord side)
Physical characteristics	Dimensions 17.32(w) x 14.17(d) x 1.72(h) in (44.00 x 36.00 x 4.37 cm) (1U height) Weight 16.53 lb (7.5 kg) shipping weight
Memory and processor	2 GB SDRAM; Packet buffer size: 4 MB, 512 MB flash
Mounting and enclosure	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included)
Performance	IPv6 Ready Certified
	1000 Mb Latency < 5 µs
	10 Gbps Latency < 3 µs
	Throughput up to 214 Mpps
	Routing/Switching capacity 288 Gbps
	Routing table size 32768 entries (IPv4), 16384 entries (IPv6)
	MAC address table size 32768 entries
Environment	Operating temperature 32°F to 113°F (0°C to 45°C) Operating relative humidity 10% to 90%, noncondensing Nonoperating/Storage temperature -40°F to 158°F (-40°C to 70°C) Nonoperating/Storage relative humidity 5% to 95%, noncondensing Acoustic Low-speed fan: 52.8 dB, High-speed fan: 66.7 dB; ISO 7779
Electrical characteristics	Frequency 50/60 H Maximum heat dissipation 365 BTU/hr (385.08 kJ/hr), Ranges from 167 BTU/hr to 392 BTU/hr, depending on power supply configuration Voltage 100 - 240 VAC, rated (90 - 264 VAC, max) -48 to -60 VDC, rated (-36 to -72 VDC, max) (Depending on power supply chosen) Maximum power rating 107 W Idle power 55 W Notes Idle power is the actual power consumption of the device with no ports connected.

QuickSpecs**Technical Specifications**

Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.

Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; EN 60950-1; CAN/CSA-C22.2 No. 60950-1; FDA 21 CFR Subchapter J; ROHS Compliance; AS/NZS 60950-1; GB 4943; EAC (EurAsian Conformity Certification)
Emissions	EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; EN 61000-4-11:2004; ANSI C63.4-2009; EN 61000-3-3:2008; VCCI V-3/2012.04; EN 61000-3-2:2006+A1:2009+A2:2009 ; EN 61000-4-3:2006; EN 61000-4-4:2012; EN 61000-4-5:2006; EN 61000-4-6:2009; CISPR 22:2008 Class A; EN 55022:2010 Class A; EN 61000-4-29: 2000; CISPR 24:2010; EN 300 386 V1.6.1; VCCI V-3/2013.04 Class A
Immunity	Generic EN 55024 ESD EN300 386
Management	IMC - Intelligent Management Center; Command-line interface; Web browser; SNMP manager
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE 5510 48G 4SFP+ HI 1-slot Switch (JH146A)

I/O ports and slots	48 RJ-45 autosensing 10/100/1000 ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T); Media Type: Auto-MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only; Ports 1 - 8 support MACSec 4 SFP+ 10GbE ports 1 port expansion module slot Supports a maximum of 6 SFP+ ports or 2 1/10GBASE-T ports or 2 40GbE ports, with optional module
Additional ports and slots	1 dual-personality (RJ-45 or USB micro-B) serial console port 1 RJ-45 out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	Airflow direction is Front (port side) to Back (power cord side)
Physical characteristics	Dimensions 17.32(w) x 14.17(d) x 1.72(h) in (44.0 x 36.0 x 4.37 cm) (1U height) Weight 16.53 lb (7.5 kg)
Memory and processor	2 GB SDRAM; Packet buffer size: 4 MB, 512 MB flash
Mounting and enclosure	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included)
Performance	IPv6 Ready Certified 1000 Mb Latency < 5 µs 10 Gbps Latency < 3 µs Throughput up to 250 Mpps Routing/Switching capacity 336 Gbps Routing table size 32768 entries (IPv4), 16384 entries (IPv6) MAC address table size 32768 entries Operating temperature 32°F to 113°F (0°C to 45°C) Operating relative humidity 10% to 90%, noncondensing Nonoperating/Storage -40°F to 158°F (-40°C to 70°C)
Environment	

QuickSpecs**Technical Specifications**

	temperature	
	Nonoperating/Storage	5% to 95%, noncondensing
	relative humidity	
	Acoustic	Low-speed fan: 49.9 dB; High-speed fan: 64.8 dB; ISO 7779
Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	238 BTU/hr (686.81 kJ/hr), Ranges from 201 BTU/hr to 443 BTU/hr, depending on power supply configuration
	Voltage	100 - 240 VAC, rated (90 - 264 VAC, max) -48 to -60 VDC, rated (-36 to -72 VDC, max) (depending on power supply chosen)
	Maximum power rating	150 W
	Idle power	70 W
	Notes	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.
Safety		UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; EN 60950-1; CAN/CSA-C22.2 No. 60950-1; FDA 21 CFR Subchapter J; ROHS Compliance; AS/NZS 60950-1; GB 4943; EAC (EurAsian Conformity Certification)
Emissions		EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; EN 61000-4-11:2004; ANSI C63.4-2009; EN 61000-3-3:2008; VCCI V-3/2012.04; EN 61000-3-2:2006+A1:2009+A2:2009; EN 61000-4-3:2006; EN 61000-4-4:2012; EN 61000-4-5:2006; EN 61000-4-6:2009; CISPR 22:2008 Class A; EN 55022:2010 Class A; EN 61000-4-29: 2000; CISPR 24:2010; EN 300 386 V1.6.1; VCCI V-3/2013.04 Class A
Immunity	Generic	EN 55024
	ESD	EN300 386
Management		IMC - Intelligent Management Center; Command-line interface; Web browser; SNMP manager
Services		Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch (JH147A)

I/O ports and slots	24 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Media Type: Auto-MDIX; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only; Ports 1 - 8 support MACSec 4 SFP+ 10GbE ports 1 port expansion module slot Supports a maximum of 6 SFP+ ports or 2 1/10GBASE-T ports or 2 40GbE ports, with optional module
Additional ports and slots	1 dual-personality (RJ-45 or USB micro-B) serial console port 1 RJ-45 out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	Airflow direction is Front (port side) to Back (power cord side)
Physical characteristics	Dimensions 17.32(w) x 18.11(d) x 1.72(h) in (43.99 x 46 x 4.37 cm) (1U height)

QuickSpecs**Technical Specifications**

Memory and processor	2 GB SDRAM; Packet buffer size: 4 MB, 512 MB flash
Mounting and enclosure	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included)
Performance	IPv6 Ready Certified
	1000 Mb Latency < 5 µs
	10 Gbps Latency < 3 µs
	Throughput up to 214 Mpps
	Routing/Switching capacity 288 Gbps
	Routing table size 32768 entries (IPv4), 16384 entries (IPv6)
	MAC address table size 32768 entries
Environment	Operating temperature 32°F to 113°F (0°C to 45°C)
	Operating relative humidity 10% to 90%, noncondensing
	Nonoperating/Storage temperature -40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity 5% to 95%, noncondensing
	Acoustic Low-speed fan: 57.6 dB, High-speed fan: 66.9 dB; ISO 7779
Electrical characteristics	Frequency 50/60 Hz
	Maximum heat dissipation 2217 BTU/hr (3599.66 kJ/hr), Ranges from 228 BTU/hr to 3412 BTU/hr, depending on power supply configuration
	Voltage 100 - 240 VAC, rated (90 - 264 VAC, max)
	Maximum power rating 650 W
	Idle power 67 W
	PoE power 740 W PoE+
	Notes Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated. PoE+ power range is from 450W to 740W. PoE+ power is the power supplied by the internal power supply(ies). It is dependent on the type and quantity of power supplies. Device supports 1 or 2 internal modular power supplies.
Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; EN 60950-1; CAN/CSA-C22.2 No. 60950-1; FDA 21 CFR Subchapter J; ROHS Compliance; AS/NZS 60950-1; GB 4943; EAC (EurAsian Conformity Certification)
Emissions	EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; EN 61000-4-11:2004; ANSI C63.4-2009; EN 61000-3-3:2008; VCCI V-3/2012.04; EN 61000-3-2:2006+A1:2009+A2:2009 ; EN 61000-4-3:2006; EN 61000-4-4:2012; EN 61000-4-5:2006; EN 61000-4-6:2009; CISPR 22:2008 Class A; EN 55022:2010 Class A; EN 61000-4-29: 2000; CISPR 24:2010; EN 300 386 V1.6.1; VCCI V-3/2013.04 Class A
Immunity	Generic EN 55024
	ESD EN300 386
Management	IMC - Intelligent Management Center; Command-line interface; Web browser; SNMP manager

QuickSpecs**Technical Specifications****Services**

Refer to the Hewlett Packard Enterprise website at <http://www.hpe.com/networking/services> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch (JH148A)**I/O ports and slots**

48 RJ-45 autosensing 10/100/1000 PoE+ ports (IEEE 802.3 Type 10BASE-T, IEEE 802.3u Type 100BASE-TX, IEEE 802.3ab Type 1000BASE-T, IEEE 802.3at PoE+); Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only; Ports 1 - 8 support MACSec
4 SFP+ 10GbE ports
1 port expansion module slot

Supports a maximum of 6 SFP+ ports or 2 1/10GBASE-T ports or 2 40GbE ports, with optional module

Additional ports and slots

1 dual-personality (RJ-45 or USB micro-B) serial console port
1 RJ-45 out-of-band management port
1 USB 2.0

Power supplies

2 power supply slots
1 minimum power supply required (ordered separately)

Fan tray

Airflow direction is Front (port side) to Back (power cord side)

Physical characteristics

Dimensions 17.32(w) x 18.11(d) x 1.72(h) in (43.99 x 46 x 4.37 cm) (1U height)
Weight 27.56 lb (12.5 kg) shipping weight

Memory and processor

2 GB SDRAM; Packet buffer size: 4 MB, 512 MB flash

Mounting and enclosure

Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included)

Performance

IPv6 Ready Certified

1000 Mb Latency < 5 µs

10 Gbps Latency < 3 µs

Throughput up to 250 Mpps

Routing/Switching capacity 336 Gbps

Routing table size 32768 entries (IPv4), 16384 entries (IPv6)

MAC address table size 32768 entries

Environment

Operating temperature 32°F to 113°F (0°C to 45°C)

Operating relative humidity 10% to 90%, noncondensing

Nonoperating/Storage temperature -40°F to 158°F (-40°C to 70°C)

Nonoperating/Storage relative humidity 5% to 95%, noncondensing

Acoustic Low-speed fan: 57.6 dB, High-speed fan: 66.9 dB; ISO 7779

Electrical characteristics

Frequency 50/60 Hz

Maximum heat dissipation 2286 BTU/hr (2411.73 kJ/hr), Heat dissipation ranges from 256 BTU/hr to 6142 BTU/hr, depending on power supply configuration

Voltage 100 - 240 VAC, rated (90 - 264 VAC, max)

Maximum power rating 670 W

Idle power 75 W

PoE power 1440 W PoE+

Notes **Idle power is the actual power consumption of the device with no ports connected.**

QuickSpecs**Technical Specifications**

Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.

PoE+ power range is from 450W to 1440W. PoE+ power is the power supplied by the internal power supply(ies). It is dependent on the type and quantity of power supplies.

Device supports 1 or 2 internal modular power supplies.

Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; EN 60950-1; CAN/CSA-C22.2 No. 60950-1; FDA 21 CFR Subchapter J; ROHS Compliance; AS/NZS 60950-1; GB 4943; EAC (EurAsian Conformity Certification)
Emissions	EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; EN 61000-4-11:2004; ANSI C63.4-2009; EN 61000-3-3:2008; VCCI V-3/2012.04; EN 61000-3-2:2006+A1:2009+A2:2009 ; EN 61000-4-3:2006; EN 61000-4-4:2012; EN 61000-4-5:2006; EN 61000-4-6:2009; CISPR 22:2008 Class A; EN 55022:2010 Class A; EN 61000-4-29: 2000; CISPR 24:2010; EN 300 386 V1.6.1; VCCI V-3/2013.04 Class A
Immunity	Generic EN 55024 ESD EN300 386
Management	IMC - Intelligent Management Center; Command-line interface; Web browser; SNMP manager
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.

HPE 5510 24G SFP 4SFP+ HI 1-slot Switch (JH149A)

I/O ports and slots	16 fixed Gigabit Ethernet SFP ports; Ports 1 - 8 support MACSec 8 Combo GbE (SFP and RJ45) dual-personality 1000 Mbps port, IEEE 802.3ab Type 1000BASE-T; Duplex: 10BASE-T/100BASE-TX: half or full; 1000BASE-T: full only 4 SFP+ 10GbE ports 1 port expansion module slot Supports a maximum of 6 SFP+ ports or 2 1/10GBASE-T ports or 2 40GbE ports, with optional module
Additional ports and slots	1 dual-personality (RJ-45 or USB micro-B) serial console port 1 RJ-45 out-of-band management port 1 USB 2.0
Power supplies	2 power supply slots 1 minimum power supply required (ordered separately)
Fan tray	Airflow direction is Front (port side) to Back (power cord side)
Physical characteristics	Dimensions 17.32(w) x 14.17(d) x 1.72(h) in (43.99 x 35.99 x 4.37 cm) (1U height) Weight 16.53 lb (7.5 kg) shipping weight
Memory and processor	2 GB SDRAM; Packet buffer size: 4 MB, 512 MB flash
Mounting and enclosure	Mounts in an EIA standard 19-inch telco rack or equipment cabinet (hardware included)
Performance	IPv6 Ready Certified 1000 Mb Latency < 5 µs 10 Gbps Latency < 3 µs Throughput up to 214 Mpps Routing/Switching capacity 288 Gbps Routing table size 32768 entries (IPv4), 16384 entries (IPv6) MAC address table size 32768 entries

QuickSpecs**Technical Specifications**

Environment	Operating temperature	32°F to 113°F (0°C to 45°C)
	Operating relative humidity	10% to 90%, noncondensing
	Nonoperating/Storage temperature	-40°F to 158°F (-40°C to 70°C)
	Nonoperating/Storage relative humidity	5% to 95%, noncondensing
	Acoustic	Low-speed fan: 50.5 dB; High-speed fan: 66.9 dB; ISO 7779
Electrical characteristics	Frequency	50/60 Hz
	Maximum heat dissipation	409 BTU/hr (431.49 kJ/hr), Heat dissipation ranges from 163 BTU/hr to 498 BTU/hr, depending on power supply configuration
	Voltage	100 - 240 VAC, rated (90 - 264 VAC, max) -48 to -60 VDC, rated (-36 to -72 VDC, max) (Depending on power supply chosen)
	Maximum power rating	120 W
	Idle power	48 W
	Notes	<p>Idle power is the actual power consumption of the device with no ports connected.</p> <p>Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated.</p>
Safety	UL 60950-1; EN 60825-1 Safety of Laser Products-Part 1; EN 60825-2 Safety of Laser Products-Part 2; IEC 60950-1; EN 60950-1; CAN/CSA-C22.2 No. 60950-1; FDA 21 CFR Subchapter J; ROHS Compliance; AS/NZS 60950-1; GB 4943; EAC (EurAsian Conformity Certification)	
Emissions	EMC Directive 2004/108/EC; FCC (CFR 47, Part 15) Class A; EN 61000-4-11:2004; ANSI C63.4-2009; EN 61000-3-3:2008; VCCI V-3/2012.04; EN 61000-3-2:2006+A1:2009+A2:2009 ; EN 61000-4-3:2006; EN 61000-4-4:2012; EN 61000-4-5:2006; EN 61000-4-6:2009; CISPR 22:2008 Class A; EN 55022:2010 Class A; EN 61000-4-29: 2000; CISPR 24:2010; EN 300 386 V1.6.1; VCCI V-3/2013.04 Class A	
Immunity	Generic	EN 55024
	ESD	EN300 386
Management	IMC - Intelligent Management Center; Command-line interface; Web browser; SNMP manager	
Services	Refer to the Hewlett Packard Enterprise website at http://www.hpe.com/networking/services for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

Standards and protocols (applies to all products in series)

BGP	RFC 1657 Definitions of Managed Objects for BGPv4 RFC 1771 BGPv4 RFC 2385 BGP Session Protection via TCP MD5 RFC 2858 BGP-4 Multi-Protocol Extensions
Device Management	RFC 1155 Structure and Mgmt Information (SMIv1) RFC 1157 SNMPv1/v2c RFC 1305 NTPv3 RFC 2573 (SNMPv3 Applications)

QuickSpecs**Technical Specifications**

RFC 2578-2580 SMIv2
RFC 2819 (RMON groups Alarm, Event, History and Statistics only)
RFC 3416 (SNMP Protocol Operations v2)
RFC 3417 (SNMP Transport Mappings)
HTML and telnet management
Multiple Configuration Files
SNMP v3 and RMON RFC support
SSHv1/SSHv2 Secure Shell
TACACS/TACACS+
Web UI

General Protocols

IEEE 802.1ad Q-in-Q
IEEE 802.1ak Multiple Registration Protocol (MRP) and Multiple VLAN Registration Protocol (MVRP)
IEEE 802.1AX-2008 Link Aggregation
IEEE 802.1D MAC Bridges
IEEE 802.1p Priority
IEEE 802.1Q (GVRP)
IEEE 802.1Q VLANs
IEEE 802.1s Multiple Spanning Trees
IEEE 802.1v VLAN classification by Protocol and Port
IEEE 802.1w Rapid Reconfiguration of Spanning Tree
IEEE 802.1X PAE
IEEE 802.3 Type 10BASE-T
IEEE 802.3ab 1000BASE-T
IEEE 802.3ac (VLAN Tagging Extension)
IEEE 802.3ad Link Aggregation (LAG)
IEEE 802.3ad Link Aggregation Control Protocol (LACP)
IEEE 802.3ae 10-Gigabit Ethernet
IEEE 802.3af Power over Ethernet
IEEE 802.3at Power over Ethernet Plus
IEEE 802.3az Energy Efficient Ethernet
IEEE 802.3i 10BASE-T
IEEE 802.3u 100BASE-X
IEEE 802.3x Flow Control
IEEE 802.3z 1000BASE-X
RFC 768 UDP
RFC 783 TFTP Protocol (revision 2)
RFC 791 IP
RFC 792 ICMP
RFC 793 TCP
RFC 826 ARP
RFC 854 TELNET
RFC 855 Telnet Option Specification
RFC 894 IP over Ethernet
RFC 925 Multi-LAN Address Resolution
RFC 950 Internet Standard Subnetting Procedure
RFC 951 BOOTP
RFC 1027 Proxy ARP
RFC 1042 IP Datagrams
RFC 1058 RIPv1
RFC 1071 Computing the Internet Checksum
RFC 1122 Requirements for Internet Hosts - Communication Layers
RFC 1123 Requirements for Internet Hosts
RFC 1141 Incremental updating of the Internet checksum
RFC 1191 Path MTU discovery

QuickSpecs**Technical Specifications**

RFC 1213 Management Information Base for Network Management of TCP/IP-based internets
RFC 1305 NTPv3
RFC 1350 TFTP Protocol (revision 2)
RFC 1519 CIDR
RFC 1533 DHCP Options and BOOTP Vendor Extensions
RFC 1542 BOOTP Extensions
RFC 1591 DNS (client only)
RFC 1723 RIP v2
RFC 1812 IPv4 Routing
RFC 1866 Hypertext Markup Language - 2.0
RFC 1887 An Architecture for IPv6 Unicast Address Allocation
RFC 2131 DHCP
RFC 2236 IGMP Snooping
RFC 2338 VRRP
RFC 2375 IPv6 Multicast Address Assignments
RFC 2462 IPv6 Stateless Address Autoconfiguration
RFC 2474 Definition of the Differentiated Services Field (DS Field) in the IPv4 and IPv6 Headers
RFC 2475 Architecture for Differentiated Services
RFC 2597 Assured Forwarding PHB Group
RFC 2616 Hypertext Transfer Protocol -- HTTP/1.1
RFC 2644 Directed Broadcast Control
RFC 2665 Definitions of Managed Objects for the Ethernet-like Interface Types
RFC 2668 Definitions of Managed Objects for IEEE 802.3 Medium Attachment Units (MAUs)
RFC 2711 IPv6 Router Alert Option
RFC 2784 Generic Routing Encapsulation (GRE)
RFC 2865 Remote Authentication Dial In User Service (RADIUS)
RFC 2866 RADIUS Accounting
RFC 2868 RADIUS Attributes for Tunnel Protocol Support
RFC 3209 RSVP-TE Extensions to RSVP for LSP Tunnels
RFC 3246 Expedited Forwarding PHB
RFC 3410 Applicability Statements for SNMP
RFC 3414 User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3)
RFC 3415 View-based Access Control Model (VACM) for the Simple Network Management Protocol (SNMP)
RFC 3416 Protocol Operations for SNMP
RFC 3417 Transport Mappings for the Simple Network Management Protocol (SNMP)
RFC 3418 Management Information Base (MIB) for the Simple Network Management Protocol (SNMP)
RFC 3484 Default Address Selection for Internet Protocol version 6 (IPv6)
RFC 3493 Basic Socket Interface Extensions for IPv6
RFC 3542 Advanced Sockets Application Program Interface (API) for IPv6
RFC 3576 Ext to RADIUS (CoA only)
RFC 3587 IPv6 Global Unicast Address Format
RFC 3596 DNS Extensions to Support IP Version 6
RFC 3623 Graceful OSPF Restart
RFC 3704 Unicast Reverse Path Forwarding (URPF)
RFC 3768 Virtual Router Redundancy Protocol (VRRP)
RFC 3810 Multicast Listener Discovery Version 2 (MLDv2) for IPv6
RFC 4090 Fast Reroute Extensions to RSVP-TE for LSP Tunnels
RFC 4113 Management Information Base for the User Datagram Protocol (UDP)
RFC 4213 Basic IPv6 Transition Mechanisms
RFC 4250 The Secure Shell (SSH) Protocol Assigned Numbers
RFC 4251 The Secure Shell (SSH) Protocol Architecture
RFC 4252 The Secure Shell (SSH) Authentication Protocol
RFC 4253 The Secure Shell (SSH) Transport Layer Protocol

QuickSpecs**Technical Specifications**

RFC 4254 The Secure Shell (SSH) Connection Protocol
 RFC 4291 IP Version 6 Addressing Architecture
 RFC 4443 Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification
 RFC 4541 Considerations for Internet Group Management Protocol (IGMP) and Multicast Listener Discovery (MLD) Snooping Switches
 RFC 4575 A Session Initiation Protocol (SIP) Event Package for Conference State
 RFC 4594 Configuration Guidelines for DiffServ Service Classes
 RFC 4675 RADIUS VLAN & Priority
 RFC 4750 OSPF Version 2 Management Information Base
 RFC 4762 Virtual Private LAN Service (VPLS) Using Label Distribution Protocol (LDP) Signaling
 RFC 5095 Deprecation of Type 0 Routing Headers in IPv6
 802.1r - GARP Proprietary Attribute Registration Protocol (GPRP)

IP Multicast

RFC 1112 IGMPv1
 RFC 2236 IGMPv2
 RFC 2710 Multicast Listener Discovery (MLD) for IPv6
 RFC 2858 Multiprotocol Extensions for BGP-4
 RFC 3376 IGMPv3
 RFC 3569 An Overview of Source-Specific Multicast (SSM)
 RFC 3618 Multicast Source Discovery Protocol (MSDP)
 RFC 3973 PIM Dense Mode
 RFC 4601 PIM Sparse Mode

IPv6

RFC 1981 IPv6 Path MTU Discovery
 RFC 2460 IPv6 Specification
 RFC 2461 IPv6 Neighbor Discovery
 RFC 2463 ICMPv6
 RFC 2464 Transmission of IPv6 over Ethernet Networks
 RFC 3162 RADIUS and IPv6
 RFC 3306 Unicast-Prefix-based IPv6 Multicast Addresses
 RFC 3307 IPv6 Multicast Address Allocation
 RFC 3315 DHCPv6 (client and relay)
 RFC 3484 Default Address Selection for IPv6
 RFC 3736 Stateless Dynamic Host Configuration Protocol (DHCP) Service for IPv6
 RFC 4291 IP Version 6 Addressing Architecture
 RFC 4293 MIB for IP
 RFC 4443 ICMPv6
 RFC 4861 IPv6 Neighbor Discovery
 RFC 4862 IPv6 Stateless Address Auto-configuration

MIBs

RFC 1212 Concise MIB Definitions
 RFC 1213 MIB II
 RFC 1215 A Convention for Defining Traps for use with the SNMP
 RFC 1493 Bridge MIB
 RFC 1757 Remote Network Monitoring MIB
 RFC 2096 IP Forwarding Table MIB
 RFC 2233 Interface MIB
 RFC 2571 SNMP Framework MIB
 RFC 2572 SNMP-MPD MIB
 RFC 2573 SNMP-Notification MIB
 RFC 2573 SNMP-Target MIB
 RFC 2574 SNMP USM MIB
 RFC 2618 RADIUS Authentication Client MIB

QuickSpecs**Technical Specifications**

RFC 2620 RADIUS Accounting Client MIB
 RFC 2665 Ethernet-Like-MIB
 RFC 2668 802.3 MAU MIB
 RFC 2674 Definitions of Managed Objects for Bridges with Traffic Classes, Multicast Filtering, and Virtual Extensions
 RFC 2737 Entity MIB (Version 2)
 RFC 2819 RMON MIB
 RFC 2863 The Interfaces Group MIB
 RFC 2925 Ping MIB
 RFC 3414 SNMP-User based-SM MIB
 RFC 3415 SNMP-View based-ACM MIB
 RFC 3418 MIB for SNMPv3
 RFC 3621 Power Ethernet MIB

MPLS RFC 2961 RSVP Refresh Overhead Reduction Extensions
 RFC 3031 Multiprotocol Label Switching Architecture
 RFC 3032 MPLS Label Stack Encoding
 RFC 3036 LDP Specification
 RFC 4762 Virtual Private LAN Service (VPLS) Using Label Distribution Protocol (LDP) Signaling

Network Management IEEE 802.1AB Link Layer Discovery Protocol (LLDP)
 RFC 1215 Convention for defining traps for use with the SNMP
 RFC 2579 Textual Conventions for SMIv2
 RFC 2580 Conformance Statements for SMIv2
 RFC 2818 HTTP over TLS
 RFC 2819 Four groups of RMON: 1 (statistics), 2 (history), 3 (alarm) and 9 (events)
 RFC 6398 IP Router Alert Considerations and Usage
 ANSI/TIA-1057 LLDP Media Endpoint Discovery (LLDP-MED)
 SNMPv1/v2c/v3

OSPF RFC 1587 OSPF NSSA
 RFC 1850 OSPFv2 Management Information Base (MIB), traps
 RFC 2328 OSPFv2
 RFC 2370 OSPF Opaque LSA Option

QoS/CoS RFC 2474 DS Field in the IPv4 and IPv6 Headers
 RFC 3260 New Terminology and Clarifications for DiffServ

Security IEEE 802.1X Port Based Network Access Control
 RFC 1492 TACACS+
 RFC 2138 RADIUS Authentication
 RFC 2139 RADIUS Accounting
 RFC 2865 RADIUS Authentication
 RFC 2866 RADIUS Accounting
 RFC 3260 New Terminology and Clarifications for DiffServ
 RFC 4716 SSH Public Key File Format
 Secure Sockets Layer (SSL)
 SSHv2 Secure Shell

QuickSpecs**Accessories****HPE FlexNetwork 5510 HI Switch Series accessories****Modules**

HPE 5510 2-port QSFP+ Module	JH155A
HPE 5130/5510 10GBASE-T 2-port Module ¹	JH156A
HPE 5130/5510 10GbE SFP+ 2-port Module ¹	JH157A

Transceivers

HPE X115 100M SFP LC BX 10-U Transceiver ²	JD100A
HPE X115 100M SFP LC BX 10-D Transceiver ²	JD101A
HPE X115 100M SFP LC FX Transceiver ²	JD102B
HPE X110 100M SFP LC LX Transceiver ²	JD120B
HPE X125 1G SFP LC LH40 1310nm Transceiver ³	JD061A
HPE X120 1G SFP LC LH40 1550nm Transceiver ³	JD062A
HPE X125 1G SFP LC LH70 Transceiver ³	JD063B
HPE X120 1G SFP RJ45 T Transceiver ³	JD089B
HPE X120 1G SFP LC BX 10-U Transceiver ³	JD098B
HPE X120 1G SFP LC BX 10-D Transceiver ³	JD099B
HPE X120 1G SFP LC LH100 Transceiver ³	JD103A
HPE X120 1G SFP LC SX Transceiver ³	JD118B
HPE X120 1G SFP LC LX Transceiver ³	JD119B
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE X130 10G SFP+ LC ER 40km Transceiver ⁴	JG234A
HPE X130 10G SFP+ LC LH 80km Transceiver ⁴	JG915A
HPE X130 10G SFP+ LC LRM Transceiver ⁴	JD093B
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X130 10G SFP+ LC LH80 tunable Transceiver	JL250A

Cables

HPE LC to LC Multi-mode OM3 2-Fiber 0.5m 1-Pack Fiber Optic Cable	AJ833A
HPE LC to LC Multi-mode OM3 2-Fiber 1.0m 1-Pack Fiber Optic Cable	AJ834A

QuickSpecs**Accessories**

HPE LC to LC Multi-mode OM3 2-Fiber 2.0m 1-Pack Fiber Optic Cable	AJ835A
HPE LC to LC Multi-mode OM3 2-Fiber 5.0m 1-Pack Fiber Optic Cable	AJ836A
HPE LC to LC Multi-mode OM3 2-Fiber 15.0m 1-Pack Fiber Optic Cable	AJ837A
HPE LC to LC Multi-mode OM3 2-Fiber 30.0m 1-Pack Fiber Optic Cable	AJ838A
HPE LC to LC Multi-mode OM3 2-Fiber 50.0m 1-Pack Fiber Optic Cable	AJ839A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 1m Cable	QK732A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 2m Cable	QK733A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 5m Cable	QK734A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 15m Cable	QK735A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 30m Cable	QK736A
HPE Premier Flex LC/LC Multi-mode OM4 2 fiber 50m Cable	QK737A

HPE 5510 24G 4SFP+ HI 1-slot Switch (JH145A)

HPE FlexNetwork 5500 150WAC Power Supply ⁵	JD362A
HPE FlexNetwork 5500 150WDC Power Supply ⁵	JD366A

HPE 5510 48G 4SFP+ HI 1-slot Switch (JH146A)

HPE FlexNetwork 5500 150WAC Power Supply ⁵	JD362A
HPE FlexNetwork 5500 150WDC Power Supply ⁵	JD366A

HPE 5510 24G PoE+ 4SFP+ HI 1-slot Switch (JH147A)

HPE X362 720W 100-240VAC to 56VDC PoE Power Supply ⁵	JG544A
HPE X362 1110W 115-240VAC to 56VDC PoE Power Supply ⁵	JG545A

HPE 5510 48G PoE+ 4SFP+ HI 1-slot Switch (JH148A)

HPE X362 720W 100-240VAC to 56VDC PoE Power Supply ⁵	JG544A
HPE X362 1110W 115-240VAC to 56VDC PoE Power Supply ⁵	JG545A

HPE 5510 24G SFP 4SFP+ HI 1-slot Switch (JH149A)

HPE FlexNetwork 5500 150WAC Power Supply ⁵	JD362A
HPE FlexNetwork 5500 150WDC Power Supply ⁵	JD366A

¹ Module supports MACsec² Supported only on JH149A (HPE 5510 24G SFP 4SFP+ HI 1-Slot Switch) and only in 1G downlink configuration³ Transceiver cannot be used on optional module JH157A (HPE 5130/5510 10GbE SFP+ 2-port Module)⁴ Supported only on optional module JH157A⁵ Products covered by 1 year warranty. See details at www.hpe.com/networking/warrantyquickref

QuickSpecs**Summary of Changes**

Date	Version History	Action	Description of Change
19-Aug-2016	From Version 7 to 8	Changed	Updates made on Standards and protocols, Configuration and Accessories
01-Aug-2016	From Version 6 to 7	Added	SKU added: JL250A
		Changed	Updates made on Technical Specifications
20-May-2016	From Version 5 to 6	Changed	Updates made on Technical Specifications and Accessories
08-Apr-2016	From Version 4 to 5	Changed	Changes made on Configuration section, SKUs descriptions updated
16-Feb-2016	From Version 3 to 4	Changed	Configuration and Standards and protocols updated
08-Jan-2016	From Version 2 to 3	Changed	Accessories section updated
11-Dec-2015	From Version 1 to 2	Changed	Transceivers updated.



[**Sign up for updates**](#)

© Copyright 2016 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: [**http://www.hpe.com/networking**](http://www.hpe.com/networking)

c04843027 - 15440 - Worldwide - V8 - 19-August-2016

