

# DIVAR IP 2000

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Fully featured video recording solution for up to 16 channels
- ▶ Out-of-the-box IP video recording solution with up to 8 TB (4 x 2 TB) storage capacity
- ▶ Robust, secure operation – instant real time access to video
- ▶ Instantly find what you are looking for
- ▶ Remote viewing via Video Security App and Video Client by Bosch

DIVAR IP 2000 is an affordable, easy to use all-in-one recording and management solution for network surveillance systems of up to 16 channels (all channels pre-licensed). Running the full Bosch recording solution including the Video Streaming Gateway to integrate 3<sup>rd</sup> party cameras, DIVAR IP 2000 is an intelligent IP storage device that provides both, a professional video recording solution and ease of operation.

DIVAR IP 2000 is a 4-bay mini tower unit that combines advanced management and state-of-the-art recording management into a single cost-effective, plug and play IP recording appliance for IT-minded customers which are seeking for a state-of-the-art “second generation” NVR recording solution.

## System overview

DIVAR IP 2000 utilizes a highly energy efficient, embedded design at a very affordable price which nevertheless boasts Bosch quality through-and-through.

Easy to install and operate, the DIVAR IP 2000 system features wizard-based set-up and centralized configuration to reduce installation times by as much as 45%. All components are pre-installed and pre-

configured. Simply connect to the network and power the unit up – DIVAR IP 2000 is ready to begin recording straight out-of-the-box.

## Functions

DIVAR IP 2000 features front-swappable SATA-II hard drives providing up to 8 TB of gross storage capacity. All system software is pre-installed and pre-activated – creating an out-of-the-box ready-to-use video recording appliance. The DIVAR IP 2000 system utilizes Microsoft Windows Storage Server 2008 R2 (64-bit).

### Remote viewing

DIVAR IP 2000 comes with our advanced Video Client for remote viewing. Video Client is a Windows PC application for live viewing and playback including Configuration Manager.

Configuration Manager allows the settings of DIVAR IP 2000 be configured.

A stand-alone archive player will allow archive playback and authentication without any other workstation software.

### Instant real time access to video

View high quality HD video despite low or limited bandwidth connections. Dynamic Transcoding technology ensures you can view your video immediately – anytime, anywhere.

Dynamic Transcoding retrieves the data from DIVAR IP 2000 and subsequently decodes and decompresses the data stream to a lower rate bit stream tailored to the bandwidth of the connection. When the video is paused, the instant detail enhancement feature instantly displays the full HD video.

### IP management and monitoring

Microsoft Windows Storage Server 2008 R2 provides a simple, intuitive user interface for system configuration and unified appliance management. Administrators and IT professionals will appreciate the ability to manage DIVAR IP 2000 using the built-in Microsoft System Center Suite compatibility. The ability to use one central tool for configuration and operations management reduces installation and training requirements, and helps keep ongoing system management costs low.

### Bosch quality

Bosch subjects all its products to the most comprehensive and rigorous battery of quality endurance tests in the industry. Our recording products are subjected to extreme temperatures, voltages and vibrations to determine true operating limits, so you can be assured of long-term reliable operation. And Bosch firmly stands behind every product it sells with an end-to-end 3 year warranty backed by technical support.

### Certifications and approvals

Region	Certification	
Europe	CE	DIVAR IP 2000/3000
USA	UL	DIVAR IP 2000/3000

### Installation/configuration notes

DIVAR IP 2000 comes pre-configured in a standard non-RAID configuration and provides the following specifications:

Gross capacity	Net capacity	Bandwidth (read & write)	Cameras
w/o HDD	n/a	100 Mbit/s	16
2 x 2 TB	3700 GB	100 Mbit/s	16
4 x 2 TB	7400 GB	100 Mbit/s	16

These values refer to the Bosch Video Management System recording engine; net capacity for a non-RAID configuration; 16 connected cameras indicate the number of concurrent recordable cameras including the connected replay clients.

DIVAR IP 2000 allows a maximum of overall 16 channels: recording and replay clients.



### Notice

Bosch is not liable for system failures of units equipped with non-Bosch hard drives if the non-Bosch hard drives are source of the issues.

### Parts included

Processor	
Processor	Intel Atom D525 processor + Intel ICH 9R storage controller
Socket	1
Chipset	Intel 82801IR I/O controller hub (ICH 9R) (Southbridge)
Memory	
Memory type	DDR3 SO-DIMM
Max front side bus	1333 MHz
Memory installed	4 GB, DDR3-1333 SO-DIMM (2 x 2 GB)
Storage	
Storage type	4 trays: 3.5-inch SATA
Hard drives installed	4 x HDD (2 TB 5400RPM GP) max
Graphics	Graphics memory controller integrated in the Intel Atom D525 processor
Network	1 x 1 GbE RJ45 port
System status	

DIVAR IP 2000 family comes fully loaded and fully functional with Microsoft Operating System and Bosch application pre-installed: WSS 2008 R2, 64-bit; Bosch Video Recording Manager including Video Streaming Gateway; Dynamic Transcoding.

### Technical specifications

Electrical	
Power supply	220 W (100/240 VAC)
Energy efficiency	Energy Star compliant power supply
Power consumption	37 W max 32 W idle
Mechanical	
Form factor	4-bay mini tower
Power supply	1 x internal power supply
USB ports	3 x USB 2.0, 2 x USB 3.0 port
Network	1 x Gigabit Ethernet LAN

<b>Mechanical</b>	
Dimensions (H x W x D)	180 x 200 x 212 mm (7.09 x 7.87 x 8.35 in)
Weight	w/o HDD: 4.25 kg (9.37 lb) fully loaded: 6.75 kg (14.88 lb)
<b>Environmental</b>	
Operating temperature	+10 °C to +35 °C (+50 °F to +95 °F)
Non-operating temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Operating relative humidity	8 to 90% (non-condensing)
Non-operating relative humidity	5 to 95% (non-condensing)

### Ordering information

#### DIVAR IP 2000, 2 HDD

All-in-one recording and management solution for network surveillance systems of up to 16 channels, 2 x 2 TB storage capacity  
Order number **DIP-2042-2HD**

#### DIVAR IP 2000, 4 HDD

All-in-one recording and management solution for network surveillance systems of up to 16 channels, 4 x 2 TB storage capacity  
Order number **DIP-2042-4HD**

#### DIVAR IP 2000, w/o HDD

All-in-one recording and management solution for network surveillance systems of up to 16 channels, w/o HDD  
Order number **DIP-2040-00N**

### Accessories

#### DIVAR IP HDD

DIVAR IP 2000/3000 – 2000 GB HDD  
Order number **DIP-2302-HDD**

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com