# **FLEXIDOME IP outdoor 5000 MP**

www.boschsecurity.com







- ▶ 5MP for highly detailed images
- Easy to install with auto zoom/focus lens, wizard and pre-configured modes
- ▶ Fully configurable quad streaming
- Regions of interest and E-PTZ
- ▶ IR version with 15 m (50 ft) viewing distance

The 5MP outdoor dome cameras from Bosch are professional surveillance cameras that provide high quality images for demanding security and surveillance network requirements. These robust domes are true day/night cameras offering excellent performance day or night.

There is a version with a built-in active infrared illuminator that provides high performance in extreme low-light environments.

# System overview

Vandal resistant outdoor dome with varifocal lens Ideal for outdoor use, the IK10-rated design is suitable for installations where a vandal resistance is important. The camera is protected against water and dust to IP66 standards. The varifocal lens allows you to choose the coverage area to best suit your application. Mounting options are numerous, including surface, wall, and suspended-ceiling mounting. The automatic zoom/focus lens wizard makes it easy for an installer to accurately zoom and focus the camera for both day and night operation. The wizard is activated from the PC or from the on-board camera push button making it easy to choose the workflow that suits best. The AVF (Automatic Varifocal) feature means that the zoom can be changed without opening the camera. The automatic motorized zoom/focus adjustment with 1:1 pixel mapping ensures the camera is always accurately focused.

# Functions

# Intelligent Dynamic Noise Reduction reduces bandwidth and storage requirements

The camera uses Intelligent Dynamic Noise Reduction which actively analyzes the contents of a scene and reduces noise artifacts accordingly. The low-noise image and the efficient H.264 compression technology provide clear images while reducing bandwidth and storage by up to 50% compared to other H.264 cameras. This results in reduced-bandwidth streams that still retain a high image quality and smooth motion. The camera provides the most usable image possible by cleverly optimizing the detail-to-bandwidth ratio.

# Area-based encoding

Area-based encoding is another feature which reduces bandwidth. Compression parameters for up to eight user-definable regions can be set. This allows uninteresting regions to be highly compressed, leaving more bandwidth for important parts of the scene.

# **Bitrate optimized profile**

The average typical optimized bitrate in kbits/s for various frame rates is shown in the table:

fps	5MP	480p
12	1753	438
5	1136	284
2	489	122

#### **Multiple streams**

The innovative multi-streaming feature delivers various H.264 streams together with an M-JPEG stream. These streams facilitate bandwidth-efficient viewing and recording as well as integration with third-party video management systems.

Depending on the resolution and frame rate selected for the first stream, the second stream provides a copy of the first stream or a lower resolution stream. The third stream uses the I-frames of the first stream for recording; the fourth stream shows a JPEG image at a maximum of 10 Mbit/s.

# Two-way audio and audio alarm

Two-way audio allows the operator to communicate with visitors or intruders via an external audio line input and output. Audio detection can be used to generate an alarm if needed.

## Tamper and motion detection

A wide range of configuration options is available for alarms signaling camera tampering. A built-in algorithm for detecting movement in the video can also be used for alarm signaling.

# Storage management

Recording management can be controlled by the Bosch Video Recording Manager (VRM) or the camera can use iSCSI targets directly without any recording software.

#### Edge recording

The MicroSD card slot supports up to 2 TB of storage capacity. A microSD card can be used for local alarm recording. Pre-alarm recording in RAM reduces recording bandwidth on the network, or — if microSD card recording is used — extends the effective life of the storage medium.

# **Cloud-based services**

The camera supports time-based or alarm-based JPEG posting to four different accounts. These accounts can address FTP servers or cloud-based storage facilities (for example, Dropbox). Video clips or JPEG images can also be exported to these accounts.

Alarms can be set up to trigger an e-mail or SMS notification so you are always aware of abnormal events.

The camera can also be supplied with power from +12 VDC power supplies.

# True day/night switching

The camera incorporates mechanical filter technology for vivid daytime color and exceptional night-time imaging while maintaining sharp focus under all lighting conditions.

# Hybrid mode

An analog video output enables the camera to operate in hybrid mode. This mode provides simultaneous high resolution HD video streaming and an analog video output via an SMB connector. The hybrid functionality offers an easy migration path from legacy CCTV to a modern IP-based system.

# **Access security**

Password protection with three levels and 802.1x authentication is supported. To secure Web browser access, use HTTPS with a SSL certificate stored in the camera. The video and audio communication channels can be independently AES encrypted with 128-bit keys by installing the optional encryption site license.

# **Complete viewing software**

There are many ways to access the camera's features: using a web browser, with the Bosch Video Management System, with the free-of-charge Bosch Video Client or Video Security Client, with the video security mobile app, or via third-party software.

### Video security App

The Bosch video security mobile App has been developed to enable **Anywhere** access to HD surveillance images allowing you to view live images from any location. The App is designed to give you complete control of all your cameras, from panning and tilting to zoom and focus functions. It's like taking your control room with you.

This App, together with the separately available Bosch transcoder, will allow you to fully utilize our dynamic transcoding features so you can play back images even over low-bandwidth connections.


# System integration

The camera conforms to the ONVIF Profile S specification. Compliance with this standard guarantees interoperability between network video products regardless of manufacturer.

Third-party integrators can easily access the internal feature set of the camera for integration into large projects. Visit the Bosch Integration Partner Program (IPP) website (ipp.boschsecurity.com) for more information.

Certifications and approvals		
Standards	IEC 62471 (I	R version)
	EN 60950-1	
	UL 60950-1	
	UL 60950-22	2
	CAN/CSA-C2	2.2 NO. 60950-1-03
	CAN/CSA-C2	2.2 NO. 60950-22
	EN 50130-4	
	EN 50130-5	
	FCC Part15 S	Subpart B, Class B
	EMC directive	e 2004/108/EC
	EN 55022 cla	ass B
	EN 55024	
	AS/NZS CISP	R 22 (equal to CISPR 22)
	ICES-003 Cla	iss B
	VCCI J55022	2 V2/V3
	EN 50121-4	
	EN 60950-22	2
ONVIF compliance	EN 50132-5-	2; IEC 62676-2-3
Product certifications	CE, FCC, UL,	cUL, RCM, CB, VCCI
Ingress protection	n IP66	
Impact protectio	IK10	
Region	Certification	
Europe	CE Out	door 5MP
USA	UL Out	door 5MP

# Installation/configuration notes



# Dimensions mm (inch)

# **Parts included**

- Camera
- Screw kit
- Desiccant
- Conduit adapter kit
- Installation documentation

# **Technical specifications**

Power		
Input voltage	+12 VDC or Power-over-Ethernet (48 VDC nominal)	
Power consumption	3.8 W max. 6.3 W max. (IR version)	
PoE	IEEE 802.3af (802.3at Type 1) Power level: Class 2	
Sensor		
Туре	1/3-inch CMOS	
Total sensor pixels	2592 x 1944	
Video performance - Sensitivity		
Sensitivity – (3200K, reflectivity 89%, F1.3, 30IRE)		
• Color	0.35 lx	
• Mono	0.05 lx	

0.0 lx

• With IR

Video performance – Dynamic range	
Dynamic range	81 dB Wide Dynamic Range (WDR)
Video streaming	
Video compression	H.264 (MP); M- JPEG
Streaming	Multiple configurable streams in H.264 and M- JPEG, configurable frame rate and bandwidth. Regions of Interest (ROI)
Overall IP Delay	Min. 300 ms, Max. 850 ms
GOP structure	IP
Encoding interval	1 to 12 fps
Encoding regions	Up to 8 areas with encoder quality settings per area
Video resolution	
5MP (4:3)	2592 x 1944
1.5MP (4:3)	1440 x 1080
0.8MP (4:3)	1024 x 768
VGA	640 x 480
QVGA	320 x 240
Video functions	
Day/Night	Color, Monochrome, Auto
Adjustable picture settings	Contrast, Saturation, Brightness
White Balance	4 automatic modes, manual mode and measure
Shutter	Automatic Electronic Shutter (AES); Fixed (1/12 to 1/15000) selectable; Default shutter
Backlight compensation	On/off
Noise reduction	Intelligent Dynamic Noise Reduction with separate temporal and spatial adjustments
Contrast enhancement	On/off
Sharpness	Sharpness enhancement level selectable
Intelligent defog	Intelligent Defog automatically adjusts parameters for best picture in foggy or misty scenes (switchable)
Privacy Masking	Eight independent areas, fully programmable
Video Analysis	MOTION+
Other functions	Image mirror, Image flip, Pixel counter, Video watermarking, Display stamping, Scene modes, Location

Night vision (IR version only)		
Distance	15 m (50 ft)	
LED	10 LED high efficiency array, 850 nm	
IR intensity	Adjustable	
In Intensity	Aujustable	
Optical		
Lens type	3 to 10 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 – 360	
Lens mount	Board mounted	
Adjustment	Motorized zoom/focus	
Iris control	Automatic iris control	
Day/Night	Switched mechanical IR filter	
Horizontal field of view	27.8° - 86.8°	
Vertical field of view	20.8° - 63.4°	
Input/output		
Analog video out	SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm	
Audio line in	0.707 Vrms max, 10 kOhm typical, jack connector	
Audio line out	0.707 Vrms at 16 Ohm typical, jack connector	
Alarm input	1 input	
Alarm input activation	Short or DC 5V activation	
Alarm output	1 output	
Alarm output voltage	30 VDC, max. load 0.5 A	
Ethernet	RJ45	
Audio streaming		
Standard	G.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate	
Signal-to-Noise Ratio	>50 dB	
Audio Streaming	Full-duplex / half duplex	
Local storage		
Internal RAM	10 s pre-alarm recording	
Memory card slot	Supports up to 32 GB microSDHC / 2 TB microSDXC card. (An SD card of Class 6 or higher is recommended for HD recording)	
Recording	Continuous recording, ring recording. alarm/ events/schedule recording	

Software		
Unit discovery	IP Helper	
Unit configuration	Via web browser or Configuration Manager	
Firmware update	Remotely programmable	
Software viewing	Web browser; Video Security Client; Video Security App; Bosch Video Management System; Bosch Video Client; or third party software	
Latest firmware and software	http://downloadstore.boschsecurity.com/	
Network		
Protocols	IPv4, IPv6, UDP, TCP, HTTP, HTTPS, RTP/ RTCP, IGMP V2/V3, ICMP, ICMPv6, RTSP, FTP, Telnet, ARP, DHCP, APIPA (Auto-IP, link local address), NTP (SNTP), SNMP (V1, MIB- II), 802.1x, DNS, DNSv6, DDNS (DynDNS.org, selfHOST.de, no-ip.com), SMTP, iSCSI, UPnP (SSDP), DiffServ (QoS), LLDP, SOAP, Dropbox, CHAP, digest authentication	
Encryption	TLS 1.0, SSL, DES, 3DES	
Ethernet	10/100 Base-T, auto-sensing, half/full duplex	
Connectivity	Auto-MDIX	
Interoperability	ONVIF Profile S; GB/T 28181	
Mechanical		
3-axis adjustment (pan/tilt/rotation)	350°/130°/330°	
Dimensions	Diameter: 145 mm (5.71 in) Height: 131 mm (5.14 in)	
Weight	1102 g (2.43 lb) approx.	
Color	RAL 9004, RAL 9010	
Environmental		
Operating temperature	-30 °C to +50 °C (-22 °F to +122 °F)	
Storage temperature	-30 °C to +70 °C (-22 °F to +158 °F)	
Humidity	20% to 90% relative humidity (non condensing)	

# **Ordering information**

# FLEXIDOME IP outdoor 5000 MP

Vandal-resistant IP dome camera for outdoor MP surveillance. Automatic Varifocal 3 to 10 mm f1.3 lens; IP66; IK10; IDNR; day/night; H.264 quad-streaming; cloud services; motion/tamper/audio detection; 5MP Order number NDN-50051-A3

# FLEXIDOME IP outdoor 5000 IR

Vandal-resistant IP dome camera for outdoor MP surveillance. Automatic Varifocal 3 to 10 mm f1.3 lens; IP66; IK10; IDNR ; day/night; H.264 quad-streaming; cloud services; motion/tamper/audio detection; 5MP; infrared

Order number NDI-50051-A3

# Accessories

# NDA-LWMT-DOME Dome Wall Mount

Sturdy wall L-shaped bracket for dome cameras Order number NDA-LWMT-DOME

# **VDA-WMT-AODOME Outdoor Wall Mount**

Sturdy outdoor wall mount bracket for dome cameras (Ø166 mm)

Order number VDA-WMT-AODOME

# **VDA-PMT-AODOME Outdoor Pipe Mount**

Sturdy outdoor pipe mount bracket for dome cameras (Ø166 mm)

Order number VDA-PMT-AODOME

# LTC 9213/01 Pole Mount Adapter

Flexible pole mount adapter for camera mounts (use together with the appropriate wall mount bracket). Max. 9 kg (20 lb); 3 to 15 inch diameter pole; stainless steel straps

Order number LTC 9213/01

NDA-FMT-DOME In-ceiling mount In-ceiling flush mounting kit Order number NDA-FMT-DOME

NDA-ADT4S-MINDOME 4S Surface Mount Box

Surface mount box ( $\emptyset$ 145 mm /  $\emptyset$ 5.71 in) for dome cameras (use together with the appropriate dome adapter bracket). Order number **NDA-ADT4S-MINDOME** 

Monitor/DVR Cable SMB 0.3M

0.3 m (1 ft) analog cable, SMB (female) to BNC (female) to connect camera to coaxial cable Order number **NBN-MCSMB-03M** 

# Monitor/DVR Cable SMB 3.0M

3 m (9 ft) analog cable, SMB (female) to BNC (male) to connect camera to monitor or DVR Order number NBN-MCSMB-30M

## IP66 I/O Cable

An IP66 certified cable for easy waterproof installation Order number NDN-IOC-30M

# Represented by:

#### Americas:

Americas: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us

Europe, Middle East, Africa:

# Bosch Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Robert Bosch (SEA) Pto Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

Fax: +86 21 22182398 www.boschsecurity.com.cn

 
China:
America Latina:

Bosch (Shanghai) Security Systems Ltd.
Robert Bosch Ltda Security Systems Division

203 Building, No. 333 Fuquan Road
Via Anhanguera, Km 98

North IBP
CEP 13065-900

Changning District, Shanghai
Campinas, Sao Paulo, Brazil

200338 China
Phone: +55 19 2103 2860

Phone +86 21 22181111
Fax: +55 19 2103 2862

Crw. u86 21 321820
Interm Representation Representa latam.boschsecurity@bosch.com www.boschsecurity.com

© Bosch Security Systems 2015 | Data subject to change without notice 18490378507 | en, V8, 27. Aug 2015